












Max. Power	Short description	Picture
<b>24,000 W</b>	<p>Type <b>eUV 240-2200 C0 / eUV 240-2200 C1</b></p> <p>Power ~ 2,400 to 24,000 W, stepless</p> <p>Mains 360 to 528 V, 3-phases + PE, 50 and 60 Hz</p> <p>Lamp voltage 500 to 2,100 V</p> <p>Lamp current ~ 2.0 to 13.0 A</p> <p>Lamp arc length ~ 80 to 270 cm (30" to 106")</p>	<p>A005344 / A005365</p> 
<b>32,000 W</b>	<p>Type <b>eUV 320-2700 C0 / eUV 320-2700 C1</b></p> <p>Power ~ 3,200 to 32,000 W, stepless</p> <p>Mains 360 to 528 V, 3-phases + PE, 50 and 60 Hz</p> <p>Lamp voltage 700 to 2,500 V</p> <p>Lamp current ~ 2.0 to 16.2 A</p> <p>Lamp arc length ~ 90 to 300 cm (35" to 118")</p>	<p>A005343 / A005358</p> 
<b>34,000 W</b>	<p>Type <b>FSU 341</b></p> <p>Power ~ 4,500 to 34,000 W, stepless</p> <p>Mains 376 to 509 V, 3-phases + PE 50 and 60 Hz</p> <p>Lamp voltage nominal 1,100 to 1,360 V</p> <p>Lamp current ~ 3.0 to 26.0 A</p> <p>Lamp arc length ~ 90 to 200 cm (35" to 80"), Hg lamps ~ 90 to 190 cm (35" to 75"), doped lamps</p>	<p>A003011</p> 
<b>36,000 W</b>	<p>Type <b>eUV 360-2700 C0 / eUV 360-2700 C1</b></p> <p>Power ~ 3,600 to 36,000 W, stepless</p> <p>Mains 360 to 528 V, 3-phases + PE, 50 and 60 Hz</p> <p>Lamp voltage 700 to 2,500 V</p> <p>Lamp current ~ 2.0 to 16.2 A</p> <p>Lamp arc length ~ 90 to 300 cm (35" to 118")</p>	<p>A005345 / A005359</p> 
<b>40,000 W</b>	<p>Type <b>eUV 400-3300 C0 / eUV 400-3300 C1</b></p> <p>Power ~ 4,000 to 40,000 W, stepless</p> <p>Mains 360 to 528 V, 3-phases + PE, 50 and 60 Hz</p> <p>Lamp voltage 700 to 3,100 V</p> <p>Lamp current ~ 2.0 to 14.4 A</p> <p>Lamp arc length ~ 90 to 400 cm (35" to 157")</p>	<p>A006682 / A006683</p> 

Notes:

C0: analog input and analog/digital outputs

C1: alternatively CANopen or analog/digital inputs/outputs

Electronic Power Supplies for other burning voltages or other field bus on request.